COIN/BILL ACCEPTOR (CBA™)



)))¢

CBA-V/N, CBA-VX/N

Multi-purpose, Self-service Coin-op with Networking Connectivity Automated delivery of diagnostic alerts and cash reporting data





CBA-V/N Series with optional Credit Card Terminal and Terminal Bracket

Hardware Specifications:

| Model | Standard Colors | Dimensions (W x H x D) | Weight | Power Consumption | Network Connectivity |
|----------|--------------------|---|------------------|----------------------------|---|
| CBA V/N | Putty | 17.25 in. x 31.5 in. x 10 in. 43.82cm x 80.01cm x 25.4cm | 60 lbs. 27 Kg | 100-240VAC 50/60Hx .75A | RJ45 Ethernet for diagnostics and report delivery** |
| CBA VX/N | Black* | 17.25 in. x 31.5 in. x 10 in. 43.82cm x 80.01cm x 25.4cm | 60 lbs. 27 Kg | 100-240VAC 50/60Hx .75A | RJ45 Ethernet for diagnostics and report delivery** |

*CBA VX/N available in putty by special order

** Requires connection to an SMTP mail server. USB for loading/downloading system configuration.

Currency:

| Coins | Bills/Notes | Tubes | Max Change* |
|---------------------|---|---|--|
| .05, .10, .25, 1 | 1, 5, 10, 20 | 3 (.05, .10, .25) | \$33.95 |
| | | 5 | \$111.40 |
| | | 6 | \$189.60 |
| .05, .10, .25, 1, 2 | 5, 10, 20 | 5 | |
| | | 6 | |
| .05, .10, .20, 1, 2 | 5, 10, 20 | 6 | |
| | .05, .10, .25, 1 .05, .10, .25, 1, 2 | .05, .10, .25, 1 .05, .10, .25, 1, 2 .05, .10, .25, 1, 2 5, 10, 20 | .05, .10, .25, 1 1, 5, 10, 20 3 (.05, .10, .25) .05, .10, .25, 1, 2 5, 10, 20 5 .05, .10, .25, 1, 2 5, 10, 20 5 .05, .10, .25, 1, 2 5, 10, 20 5 .05, .10, .25, 1, 2 5, 10, 20 5 .05, .10, .25, 1, 2 5, 10, 20 5 |

*5 and 6-tube systems can vary in coin type per tube. Max change assumes a standard configuration that uses 2 tubes for \$0.25 coins.

COIN/BILL ACCEPTOR (CBA™)

Integrates directly with EnvisionWare applications:

- LPT:One[™] Print Management
- Copy Payment Manager[™] copier accounting
- EnvisionWare[®] eCommerce Services[™] fine/fee payment
- AAM[™] User Account Manager for online account revalue
- Library Document Station[™] for fax, copy, and scan

Software Features:

- Delivers diagnostic reports and cash reconciliation reporting via email (SMTP server connection required)
- Ability to email meter and system status information to defined users
- Online web tool for configuring all system settings, deliver settings via USB drive
- Administrator defined email distribution list by report type
- Two copy management configurations: pay using Copy Payment Manager application or use Dual Mode implementation which allows CBA to directly control copy functions while supporting other payment applications

Reports:

Two types of reports are provided:

- Scheduled Cash Reports can be sent to specified email addresses at designated frequencies (ex. daily, weekly, monthly, etc.). These reports include a CSV file that will allow for meter data to be integrated into a location's reconciliation process. Cash Reports also include HTML formatted tables to enable easy data interpretation.
- Event Alerts are provided to specified email addresses following the occurrence of the reported event. The data from the event is provided in an HTML format table to make it easy to interpret. In the case of a CashOut Event, the HTML table and CSV file attachment with meter information are provided.

| Cash Reports | Alerts | Report Type | Description |
|--------------|--------|----------------------|--|
| Х | | Copy Count Meters | Reports the meter counts of each type in the CBA V/N series |
| Х | | Cash Meters | Reports the cash value of each of the cash meters in the CBA V/N series |
| Х | Х | Stacked # Bills | Reports when the programmed number of bills has been stacked, and gives a breakdown of each bill type. Also reported on the periodic reports |
| | Х | Power Cycled | Reports when the CBA V/Nseries has been power cycled |
| | Х | Software Updated | Reports when the CBA V/N series has downloaded and installed new firmware |
| | Х | Bypass Used | Reports when the bypass was used and the total value of the bypass activity |
| | Х | MDB Peripheral Error | Reports if one of the coin or cash devices signaled with an error of some type. This is dependent on the coin or cash device, and the error type reporting it supports |

Scheduled Diagnostic

Includes:

- Installed non-tip base
- EnvisionWare Support including
 EnvisionWare Customer Center
- Next-day advance parts replacement

Options:

- Custom copier cable
- Integrated stored value card reader
- Credit card terminal and terminal mount (requires EnvisionWare[®] eCommerce Services[™])

Requirements: (1) RJ45 network connection, power receptacle

